



GRIZZLETM SMART EV Charger

User Manual
& Installation Guide



Grizzl-E Smart Manual v. 9.0

Model Numbers:

GRS-6-24-P

GRS-14-24-P



Grizzl-E Smart Home EV Charging Station

The Grizzl-E Smart is the Wi-Fi connected smart EV Charger built from the proven Grizzl-E design. Grizzl-E Smart has Wi-Fi connectivity and can work with any OCPP 1.6 application. It is a simple, powerful, heavy-duty, and portable electric vehicle charging station made in Canada and built to withstand the harshest conditions.

The Grizzl-E Smart comes exclusively with a 24ft Premium cable. Internal design and components of the charger have been selected to provide maximum operational life of the device and be able to withstand the elements.

Grizzl-E Smart provides up to 10 KW of power to your vehicle. Maximum current output can be set through DIP Switches to provide 16 Amps, 24 Amps, 32Amps or 40 Amps adjustable maximum current.

IMPORTANT SAFETY INSTRUCTIONS

This document contains instructions and warnings that must be followed when installing and using the Grizzl-E Smart Electric Vehicle Supply Equipment (EVSE). Before installing or using the EVSE, read this document including any WARNING and CAUTION symbols.

The Symbols Used Have the Following Meanings



Warning: risk of personal injury



Warning: risk of fire



Warning: risk of electric shock



Caution: risk of damage to equipment

- This document provides instructions for the charging station and should not be used for any other product. Before installation or use of this product, review this manual carefully and consult with a licensed contractor, licensed electrician, or trained installation expert to ensure compliance with local building codes and safety standards.
- Consult a licensed electrician to ensure that you can safely install and use this product.
- Ensure that the materials used, and the installation procedures, follow local building codes and safety standards.
- The information provided in this manual in no way exempts the user of responsibility to follow all applicable codes or safety standards.

Basic precautions should always be followed when using electrical products, including the following:

- Read all the instructions before using this product.
- Children should not use this device.
- Do not put fingers into the EV connector.
- Do not touch live electrical parts.
- Do not use this product if the flexible power cord or EV cable is ragged, has broken insulation, or any other signs of damage.
- Do not use this product if the enclosure or the EV connector is broken, cracked, open, or shows any other indication of damage.
- Improper connection of the equipment grounding conductor can result in a risk of electric shock. Check with a licensed electrician if you are in doubt as to whether the product is properly connected and grounded.

Repair and Maintenance Clause

- All United Chargers products do not require routine maintenance however, periodic inspections should be conducted to ensure that all parts remain in good working order and no damage exists.
- Do not attempt to open, disassemble, repair, tamper with, or modify any components of the products. Contact United Chargers for any repairs.



WARNING: This equipment is intended only for charging vehicles that do not require ventilation during charging. Please refer to your vehicle's owner's manual to determine ventilation requirements.



Product Features

GRIZZL-E™ Smart Electric Vehicle Charging Station (EVSE)

- J1772 AC Level 2 (208-240 VAC), 40A Continuous Rated (9.6 kW)
- Adjustable Maximum Current Output (40A, 32A, 24A, 16A) to Support Multiple Circuit Ratings (50A, 40A, 30A, 20A)
- Extreme Duty, Rigid & Compact Design:
- Robust and heavy-duty aluminum cast case; airtight enclosure for indoor or outdoor use
- Wi-Fi Connectivity. Smart Charging Features.
- Compatible with all OCPP 1.6 applications.
- EasyEvPlug™ Holster or Tesla EasyEVPlug™ Holster with cable Management System.
- Plug-in Configuration for easy portability.
- Wall Mount with security features (including single stud mount), Pedestal, Bollard/Pole (Single & Dual Port) available from United Chargers.
- UL Certified

Adjustable Maximum Current Output to Support Multiple Circuit Ratings

The GRIZZL-E™ Electric Vehicle Charging Station features the ability to adjust the maximum charging station current output to allow the use of a 50A, 40A, 30A, or 20A Dedicated Circuit as follows:

50A Circuit Rating:
40A Circuit Rating:
30A Circuit Rating:
20A Circuit Rating:

To support 40A (9.6kW) Maximum Charging Station Output
To support 32A (7.68kW) Maximum Charging Station Output
To support 24A (5.76kW) Maximum Charging Station Output
To support 16A (3.84kW) Maximum Charging Station Output

The Default Factory Setting is 40A (9.6kW). To change the maximum current output, refer to Chapter 4.1 Adjust Maximum Current Output on page 12.. If you are unsure of the circuit ratings in your home consult a licensed electrician.

Self-Monitoring and Recovery | Power Outage Recovery

When a charging session is interrupted due to a temporary error condition, the charging station will automatically restart charging when the cause of the temporary error condition returns to normal. Refer to Chapter 11.3 Self-Monitoring and Recovery (Auto Restart) on page 27 for more information.

Security and Tamper Feature

In addition to the included security pin that secures the charging station to the wall mount bracket, a coupler lock and key with a length of 90mm and diameter of 7mm can also be used to lock and secure the Grizzl-E Charging Station to the wall mount.



Product Specifications

United Chargers GRIZZLE-E™ Electric Vehicle Charging Station (EVSE)

Description	Specifications
Model Numbers	GRS-6-24-P GRS-14-24-P
EVSE Level	SAE J1772; AC Level 2
Max Output Rating	40A; 9.6 kW Maximum Output – For use with 50A Circuit Rating
Alternate Adjustable Output Ratings	32A; 7.68 kW Maximum Output – For use with 40A Circuit Rating 24A; 5.76 kW Maximum Output – For use with 30A Circuit Rating 16A; 3.84 kW Maximum Output – For use with 20A Circuit Rating
Charge Cable Length	24 ft.
Electrical Circuit / Input Power Requirements	Circuit Requirement: Dedicated Single Phase 208-240VAC, 50/60 Hz.; Branch Breaker: Double pole; Circuit Conductors: Line 1, Line 2, Earth / Ground
Input Power Connection	Standard: Plug-in, NEMA 6-50 or NEMA 14-50 Plug. Plug is removable for Hardwire Connection.
Charging Station Color	Standard: Black
Installation Rating	NEMA 4, Indoor/Outdoor Rated
Operational Ratings	Temperature: -22°F to 122°F (-30°C to 50°C); Humidity: 95% RH non-condensing
Mounting	Wall or Pedestal Installation
Overall Dimensions	EVSE: 10.25 x 6.25 x 3.75 inches (26.0 x 16.0 x 9.3 cm)
Display & Indicators	LED Charge Status Indicators (Power/Ready, Charging, Fault)
Cable Management	EasyEvPlug™ with cable management
Standards & Compliance	UL Certified


INSTRUCTIONS Manual

Table of Contents


1. Introduction & Unpacking	9
2. Installation Planning and Service Wiring:	10
2.1 Electrical Source Requirements	10
2.2 Grounding Instructions	10
3. Calibrating the GRIZZL-E Unit (Optional)	11
4. Adjustable Maximum Current Output	12
4.1 Adjust Maximum Current Output.....	12
5. Installation	15
5.1 Tools & Parts Required for Installation	15
5.2 Install the Charging Station	16
6. Input Wiring Connection (Optional Hardwire Connection)	19
7. EasyEvPlug Holster and Cable Management System.....	20
8. Set Up Smart Functionality.....	21
8.1 Create account on United Chargers Portal	21
8.2 Connect the Grizzl-E to your Wi-Fi, and to OCPP Server	21
8.3 Connect to United Chargers Portal	21
8.4 Connect to Third Party OCPP Network	21
9. Re-Set Wi-Fi Board	22
9.1 Change OCPP Network	23
10. Charging Status Indicators and Buzzers	24
10.1 Charging Status Indicators	24
10.2 Fault Indicators	25
11. Operation	26
11.1 Connect and Charge	26
11.2 Stop Charging	26
11.3 Self-Monitoring and Recovery (Auto Restart)	26
12. General Product Care and Use Information	27
13. Warranty	28

1. Introduction & Unpacking


This user manual applies to the GRIZZL-E™ EVSE for Plug-in Hybrid Electric Vehicles (PHEVs) and Electric Vehicles (EVs).




Charging Station with input and output cable (x1)




Mounting Bracket (x1)




Security Pin (x1)




Robertson Head Screws (x2)




Socket Cap Screw



Holster (x1)



Phillips-head Screws (x4)



Anchor (x4)

2. Installation Planning and Service Wiring:



WARNING: Disconnect the power supply to the charging station before installing, adjusting, or repairing the charging. Failure to do so may result in physical injury or damage to the power supply system and the charging station.



CAUTION: To reduce the risk of fire, connect only to a circuit provided with the minimum branch circuit overcurrent protection requirements in accordance with the National Electrical Code ANSI/NFPA 7- and the Canadian Electrical Safety Code, Part 1, C22.1. If you are unsure if your circuit meets these requirements consult a licensed electrician.

2.1 Electrical Source Requirements

- Prior to mounting, locate an available electrical source that can support the following Input Requirements for the Charging Station Per local Electrical Safety Code requirements:
 - » 40A Maximum Output Setting (Default Factory Setting): a DEDICATED CIRCUIT rated for 50A; 208-240 VAC, 50-60 Hz, Single Phase must be used.
 - » 32A Maximum Output Setting (Optional Setting): a DEDICATED CIRCUIT rated for 40A; 208-240 VAC, 50-60 Hz, Single Phase must be used.
 - » 24A Maximum Output Setting (Optional Setting): a DEDICATED CIRCUIT rated for 30A; 208-240 VAC, 50-60 Hz, Single Phase must be used.
 - » 16A Maximum Output Setting (Optional Setting): a DEDICATED CIRCUIT rated for 20A; 208-240 VAC, 50-60 Hz, Single Phase must be used.
- A Double Pole Circuit Breaker of the circuit rating must be used.
- The Charging Unit has a built in GFCI protection; do not provide any additional GFCI protection upstream of the charging unit.
- The Charging Stations can connect a Standard NEMA 14-50 Receptacle, or the unit can be hardwired

2.2 Grounding Instructions

The charging station must be implemented equipment grounding through a permanent wiring system or an equipment grounding conductor. Use a cable with a dedicated grounding conductor connected to the equipment ground terminal block.

3. Calibrating the GRIZZL-E Unit (Optional)




WARNING: Electrical Power MUST remain OFF and DISCONNECTED before setting or changing the DIP switch. Incorrect connection may cause electric shock.

Note:

Calibration should be done before adjusting the charging station's maximum current output settings and connecting the unit to Wi-Fi.

Calibration Steps:

1. Unplug the charger and remove the front cover by removing the 4 screws at each corner of the charging station. For more information on how to remove the front cover refer to Chapter 4.1 Adjust Maximum Current Output on page 12.
2. With the front cover placed to the side, locate the DIP switch on the charging station circuit board. The DIP switch is a 4-position switch on the main circuit board, located directly to the left of the LED. Using a non-conductive object, calibrate the Grizzl-E unit by adjusting the DIP switch settings as follows:



3. Plug in the charger until the LED turns solid red. The solid red LED indicates that the calibration is finished.
4. Unplug the charger. Reset the DIP switches to the original position.
5. Plug in the charger. Ensure that LED indicator light shows Blue and Purple alternating.
6. Replace the enclosure lid by tightening the 4 screws at each corner or follow the steps from the user manual to set the maximum current output. Refer to Chapter 4.1 Adjust Maximum Current Output on page 12.

4. Adjustable Maximum Current Output

The GRIZZL-E Smart charging station features the ability to adjust the maximum Charging Station current output to support 50A, 40A, 30A, or 20A Dedicated Circuit ratings as follows:

Circuit Rating	Maximum Charging Station Output
50A	40A (9.6 kW)
40A	32A (7.68 kW)
30A	24A (5.76 kW)
20A	16A (3.84 kW)

- The Charging Station Default Factory Maximum Current Output Setting is 40A (9.6 kW) for use with a 50A Circuit Rating.
- The Circuit must be a DEDICATED CIRCUIT 208-240 VAC, 50-60 Hz, Single Phase.
- Requirements govern that only 80% of the circuit rated load may be utilized, hence the higher Circuit Ratings Requirement relative to maximum Charging Station output.

4.1 Adjust Maximum Current Output

To adjust the Maximum Current Output Setting:


1. Place the Charging Station on a flat surface with the front cover facing up.
2. Remove the front cover by removing the 4 screws at each corner of the charging station. Use a M4 Allen Key to remove the screws.









CAUTION: The LED pipe is attached to the front cover. When the front cover is removed, place it on a flat surface facing down to avoid damage to the LED pipe.

3. With the front cover placed to the side, locate the DIP switch on the charging station circuit board. The DIP switch is a 4-position switch on the main circuit board, located directly to the left of the LED.



WARNING: Do not touch live electrical parts. Disconnect the power supply to the charging station and verify no power is present before adjusting the DIP Switches. A non-conductive object **MUST** be used to adjust the DIP switch settings. Failure to do so may result in physical injury or damage to the power supply system and the charging station.

4. Using a non-conductive object adjust the Maximum Current Output to either 32A, 24A or 16A, using the following combination of DIP switch settings:

	Switch 1	Switch 2	Switch 3	Switch 4	
40A Maximum Current Output (Factory Default Setting)	UP	UP	UP	DOWN	
32A Maximum Current Output	UP	DOWN	UP	DOWN	
24A Maximum Current Output	UP	UP	DOWN	DOWN	
16A Maximum Current Output	UP	DOWN	DOWN	DOWN	

5. Once the DIP Switch Setting is adjusted, reassemble the charging station. Reinstall the top cover to the charging station using the following torque force to secure the 4 socket cap screws:

Screw	Torque
M6	16 kgf-cm 13.88 lb-in

5. Installation


5.1 Tools & Parts Required for Installation

Prior to mounting, determine the location of an acceptable mounting support. All charging station products must be anchored into a mounting support such as a 2" x 4" stud or a solid concrete wall. **DO NOT** mount this unit directly to a stucco/drywall/wall board.



Tool	Size	Source of Supply	Remark
Mounting Bracket	255 x148 x 36 mm	Included with Product	For mounting the charging station to the wall/structure
Socket cap screw (x4)	5/16"	Included with Product	For securing the charging station to the Mounting Bracket
Robertson-Head Screw (x2)	#14	Included with Product	For installing the Mounting Bracket to the wall/structure
Holster/Tesla Holster™	58 x 58 x 70 mm	Included with Product	To store the EV charging Plug and Cable
Phillips-Head Screw (x4)	#8	Included with Product	For installing the EasyEvPlug™ to the wall/structure
Anchors (x4)	#8	Included with Product	For installing the EasyEvPlug™ to the wall/structure
Philips Screwdriver	PH3	Commercially Available	For Holder Installation and Optional Hardwire Install
Allen key	M4	Commercially Available	For Charging Station Cover Screws
Allen key	3/16"	Commercially Available	For installing the enclosure plate to the back of the station body.

5.2 Install the Charging Station


1. Separate the front and back piece of the mounting bracket by pushing down on the notch.



2. Attach the front piece of the mounting bracket to the back of the charging station using the Socket-cap screws. Ensure the top of the mounting bracket is matched with the top of the charging station.



- Secure the back piece of the mounting bracket to the wall or other suitable structure using the Robertson-head screws.



The back piece of the mounting bracket has 3 holes to support attachment to various surfaces. Use the top two holes to attach the mounting bracket to a wall stud.


Mounting Screw Recommendations:

- For finished walls supported by wood studs, use #14 or M6 tapping screws. (Included).
- For masonry walls, use M6 mechanical screws. (Commercially available)
- Use following torque force:

Screw	Torque	
M6	50 kgf-cm	43.4 lb-in
1/4"	50 kgf-cm	43.4 lb-in

Mount the unit between 24 inches (0.6 m) and 48 inches (1.2 m) from the ground. The NEMA outlet should be located no less than 20~26" from the ground or as defined by applicable, local electrical safety codes and standards.

4. Mount the charger on the wall by securing the front piece of the mounting bracket to the back piece of the mounting bracket.
5. Secure the charger in place by inserting either the security pin or the outdoor security lock into the mounting bracket.



6. Plug in the power cord to the NEMA 14-50 Wall Outlet/Receptacle.

6. Input Wiring Connection (Optional Hardwire Connection)

1. Choose the appropriate conduit in accordance with all applicable, local, and electrical safety codes and standards.



2. Using the appropriate tool, clamp the wire terminal to the copper wire. For non-insulated terminals, use heat shrink tube to cover the non-insulated portion of the terminal.



3. Remove the front cover by removing the 4 screws at each corner of the charging station. For more information on how to remove the front cover refer to Chapter 4.1 Adjust Maximum Current Output on page 12.
4. With the front cover placed to the side, use Philips screwdriver to release terminal screws of the or 14-50 Plug cable. Loosen the Strain Relief Fitting for the or 14-50 Plug and Remove the Plug. Remove the Strain Relief connector.
5. Insert the wire end passing through the conduit and insert them into the input wiring hole. (Use Red wire for L1, Black wire for L2, Green wire for G). Attach the copper wire on the corresponding terminal block. Use the following wire and torque force when connecting to input terminal block.


7. EasyEvPlug Holster and Cable Management System

The EasyEvPlug™ Holster or Tesla EasyEVPlug™ Holster is the new innovative method to protect your plug and manage your cord. It has the following features:


- No need to aim – flawless plug even in the dark.
- Your EV holster will always be in a convenient location.
- Saves space – special angle for less wall clearance.
- Integrated cable management – holds up to 25 feet of cable.

The EasyEvPlug holster can be installed at any location near the charging station.


1. Hold back of holster against the mounting surface. Fasten Phillips head screws through back holes. Use anchors if attaching directly to drywall.



2. Insert charging connector into holster.



3. Wrap cable on top of EasyEvPlug.



8. Set Up Smart Functionality

Grizzl-E Smart can connect to any OCPP 1.6 compatible software.



8.1 Connect the Grizzl-E to your Wi-Fi

Note: Grizzl-E Smart is only compatible with 2.4 Ghz Wi-Fi. The Wi-Fi network must be at least 4 bars for smart features. If your computer or cell phone has less than 4 bars of Wi-Fi signal you must install a Wi-Fi repeater to increase the signal strength (5 bars full signal strength is preferred). If the signal strength is 3 bars or less, smart functionality will be unavailable.

1. Plug in the Charger.
2. Open the Wi-Fi settings on your smart phone or desktop.
3. Select the network **UC_Smart_[ChargerSerial#]**.
4. Open the browser on your device.
5. Enter the IP address 192.168.4.1 into the browser search bar.
6. A webpage will load. Select the **Enter Router Credentials** button.
7. Enter the SSID Password for your Wi-Fi network. Enter the Portal URL for the OCPP server. Follow the instructions provided by the OCPP Application provider.
8. Verify that you are connected. If connection is successful the buzzer will sound continuously for 4 seconds and indicator light will alternate between Blue and Light Blue.
9. Disconnect your smartphone from UC_Smart_#### and re-connect to your local network.
10. Close the browser page.

8.2 Connect to United Chargers OCPP Network

Create an account on acharger.ca

1. Go to the website acharger.ca.
2. Select the **Login** button.
3. Select **Sign Up** button.
4. Enter your Name, Email, Username, and Password.
5. Select the **Register** button.

Add Device to United Chargers Portal

1. Login to your account at acharger.ca.
2. Go to the Charging Stations tab.
3. Select the **Add** button from the top menu.
4. Enter the Charger Serial Number (found on the label) in the Serial Number field.
5. Select the Create button. The created charging stations will show in the Charging Station tab.


8.3 Connect to Third Party OCPP Network

1. Follow the directions on the third-party Network to configure your charging station with the OCPP central system URL.
2. Wait for connection. If connection is successful the buzzer will sound continuously for 4 seconds. If the connection is unsuccessful consult the portal provider.

9. Re-Set Wi-Fi Board

If the Grizzl-E Smart Charger has lost connection and is unable to re-establish the connection try resetting the board using the following procedure:

1. Unplug the Charging Station. Place the Charging Station on a flat surface with the front cover facing up.
2. Remove the front cover by removing the 4 screws at each corner of the charging station. For more information on how to remove the front cover refer to Chapter 4.1 Adjust Maximum Current Output on page 12
3. With the front cover placed to the side, locate the DIP switch on the charging station circuit board. The DIP switch is a 4-position switch on the main circuit board, located directly to the left of the LED.



4. Using a non-conductive object adjust the Left Switch to the down position. This applies for all amperage settings.
5. Plug the Charger back in. Wait until the LED flashes Blue/Purple alternating with 1 second frequency.
6. Unplug the Charger again.
7. Set the DIP switches back to the original position.
8. Plug the charger in. If the re-set is successful the buzzer will sound continuously for 4 seconds. Charger will display Blue/Purple alternating indicator light.
9. Replace the enclosure lid by tightening the 4 screws at each corner.
10. Follow the instructions from Chapter 8.2 Connect the Grizzl-E to your Wi-Fi, and to OCPP Server on page 21 to reconnect to your Wi-Fi network and OCPP Network.

9.1 Change OCPP Network











To Change OCPP Network to another provider:

1. Follow the instructions in Chapter 9. Re-Set Wi-Fi Board on page 23 to reset the Wi-Fi board.
2. Follow the directions on Chapter 8. Set Up Smart Functionality on page 21 and the third-party Network to configure your charging station with the OCPP central system URL.
3. Wait for connection. If connection is successful the buzzer will sound continuously for 4 seconds. If the connection is unsuccessful consult the portal provider.

10. Charging Status Indicators and Buzzers

10.1 Charging Status Indicators

The following Status Indictors will be used in both Connected Modulated and Offline Solid modes:

LED Indicator	Buzzer	Description	Definition
	No buzzer	Not illuminated	Power Off
	No buzzer	White	Initialization
	No buzzer	Blue Alternating	Ready
	No buzzer	Blue Flashing	Vehicle detected
	No buzzer	Green Flashing	Charging in progress
	No buzzer	Green Steady	Charging complete or no current consumed by the car
	Buzzer sounds continuously	Red Steady	Unrecoverable Fault
	Buzzer beeps for 5 times and then stays off	Red Flashing	Recoverable Fault
	No Buzzer	Purple Alternating*	Device is not connected to a network
	No Buzzer	Light Blue Alternating**	Device is connected to a network

*LED will alternate between Blue and Purple when the charger is ready and disconnected from the network

** LED will alternate between Blue and Light Blue when charger is ready and connected to the network

10.2 Fault Indicators

If the “Red Steady” or “Red Flashing” Fault Indicator remains use the following procedure:

1. Unplug the charging connector from your EV.
2. Turn off the power to the Charging Station by switching the upstream circuit breaker to the “OFF” position
3. With the circuit breaker in the “OFF” position, wait 1-2 minutes and then switch the upstream circuit breaker back to the “ON” position
4. Confirm the Fault light is no longer present. If the Fault light remains, please contact United Chargers technical support.

11. Operation

11.1 Connect and Charge

Insert the charging Connector into the EV and ensure the connector is fully seated/locked in place. Once complete, the charging session will begin.

Charging will start in both Connected Mode (Light Blue indicator LED) and Standard Mode (Purple indicator LED).




Figure 3-1. Connect the charging plug to the EV

11.2 Stop Charging

1. Unplug the charging station by pressing the connector button and removing the Charger Connector from the EV (once the connector button is depressed, the charging session terminates immediately).
2. Return the connector to the holster.

11.3 Self-Monitoring and Recovery (Auto Restart)

When a charging session is interrupted due to a temporary error condition, it will automatically restart charging when the cause of the temporary error condition returns to normal. The status indicator lights remain flashing RED until the error condition is resolved.

- Temporary error conditions include: Over Current, Under Voltage, Missing Diode, Ground Fault, and Over Temperature.
- For Over Current (OC) conditions: The charging session will be stopped while OC occurs. After recovery from OC for 30 seconds, the charging station will automatically restart charging for four times.
- When charging session stopped due to the Ground Fault (GFCI) trip, the charging station will try to restart after 15 minutes for 4 times. After 4 times, the charging station buzzer will stay on continuously, and status indicator will stay RED. The user should plug-out and plug-in the power cable of the charging station.

12. General Product Care and Use Information

The exterior of the charging station is designed to be waterproof and dust proof (NEMA 4 Outdoor Rated). However, periodic cleaning may be required, depending on local conditions. To ensure proper maintenance of the charging station, follow these guidelines:

- To avoid damaging the finish of the products, only use an automotive grade soft cleaning cloth with soap and water to remove accumulated dirt and dust. Do not use cleaning solvents to clean any of the product components.
- Despite the water resistance of the enclosure, submerging the unit in water is not recommended.
- Ensure the charging connector is put back in the holster after charging to avoid damage.
- Ensure the power cable is stored on the charging station after use to avoid damage.
- If the power cable or the charging connector is damaged, turn off the charging station supply circuit breaker, do not use the charging station, and Contact United Chargers Customer Support for replacement parts.
- When moving or lifting the unit, always grasp and carry by the charging station body. Never attempt to lift, move, or carry the unit by any of the electrical cables. Improper handling may cause damage to the unit.



13. Warranty

GRIZZL-E™ Smart EV Residential Charging Stations 3 Years Replacement Warranty.

Grizzl-E Smart comes with the option of a 3-year or 5-year manufacturer's warranty.

This warranty is extended by United Chargers to original purchasers of GRIZZL-E™ EV Charging Stations. United Chargers warrants that this product is free from defects in materials years and free from defects in workmanship for the period specified in the warranty from the date of purchase. No agent, employee, or representative of United Chargers has any authority to affirm, represent or warrant anything concerning GRIZZL-E™ EV Charging Stations, except for the affirmation and representation which is specifically included within this warranty.

This warranty will not apply if the product has been misused, abused, or altered. Warranty for the cable does not include normal tear and wear. Plugs that have been exposed to snow or water for a prolonged period of time are not covered by this warranty. The warranty will apply only if the product is defective. United Chargers assumes no liability for any dismantling, removal, installation, re-installation, or labor costs or any consequential damages associated with this warranty. United Chargers is not responsible or liable for any costs associated with faulty installations.

United Chargers shall make the final decision, in fairness to all concerned, as to the legitimacy of any such claim on this warranty. Upon discovery of any defective GRIZZL-E™, please contact our Customer Service Department for further instructions as to how to repair or replace the defective unit or log into your account at www.grizzl-e.com and submit support ticket.

United Chargers Inc
90 Gough Road, Unit 2
Markham, Ontario L3R 5V5 Canada

Phone: +1-833-840-4970
E-mail: info@unitedchargers.com
Website: www.grizzl-e.com

The most up to date and valid information is available at the online version of brochure, located here:
<https://grizzl-e.com/manuals/>